**HP LaserJet Pro CP1025 Color Printer series** 

Ideal for home office and small business customers who need a low-priced, compact colour laser printer with wireless and Ethernet connectivity.







### Connect wirelessly to affordable colour.

- Print from anywhere in the office and share on a network, using built-in wireless and Ethernet.<sup>1</sup>
- Save money, save space: this low-priced HP LaserJet is one of the world's smallest colour laser printers.<sup>4</sup>
- Print documents affordably. Get the same black cost per page as a black-and-white HP LaserJet printer.<sup>5</sup>
- Ensure professional, accurate results with bold text and smooth colour with HP ImageREt 2400 and Original HP cartridges with ColorSphere toner.

# Stay on task – easy mobile printing and fast setup.<sup>3</sup>

- Stay productive on the go print from virtually anywhere with HP ePrint.<sup>3</sup>
- Easily print from mobile devices without a network using wireless direct printing.<sup>6</sup> And with AirPrint<sup>™</sup> you can simply print wirelessly from your iPad<sup>®</sup>, iPhone<sup>®</sup>, and iPod touch<sup>®</sup>.<sup>7</sup>
- Install and start printing quickly and easily.
- Make maintenance easy with Original HP cartridges and a printer designed for lasting performance.

### Reduce your environmental impact.

- Conserve energy with Instant-on Technology,<sup>8</sup> and save even more with HP Auto-Off Technology.<sup>9</sup>
- Conserve resources with HP's smallest colour laser printer.
- Get free and easy recycling cartridges returned through HP Planet Partners are recycled responsibly.<sup>10</sup>
- Print only the Web content you need, neatly and accurately, with HP Smart Web Printing.<sup>11</sup>

# Create and print your own marketing materials.

- Design marketing materials and get ideas for your printed projects from HP Creative Studio for Business.
- Get the versatility you need to create a wide range of documents: print on media from 7.6 x 12.7 cm to 21.5 x 35.5 cm.
- Achieve great results: pre-configured shortcuts optimise output quality based on the media selected.

<sup>1</sup> Built-in wireless and Ethernet connectivity are available on the HP LaserJet Pro CP1025nw only. Wireless performance is dependent upon physical environment and distance from access point, and may be limited during active VPN connections. <sup>2</sup> Energy consumed based on competitive TEC measurement results found at energystar.gov and eu-energystar.org for single-function colour laser printers as of June 2010. TEC based on mono pages in mono print speed. Individual product configuration and usage will affect power consumption. <sup>3</sup> Requires an Internet connection to the printer, Feature works with any connected Internet- and email-capable device. Print times may vary. Some HP LaserJet Pro R last of supported documents, and image types, see www.hp.com/go/eprintcenter. And for additional solutions, see www.hp.com/go/mobile-printing-solutions. Available only on the HP LaserJet Pro CP1025nw Color printer. <sup>4</sup> Based on personal colour printers as defined by IDC and shipping as of June 2010 as measured by volume (WXDXH) using manufacturers' specifications or as measured by operational "Ad" size. <sup>5</sup> Compared with HP LaserJet Pro P1102/P1102W printer (single function) and HP LaserJet Pro M1132, M1136, M1212nf, M12114nfh, M12114nfh, M1214nfh, M121

Print technology	Laser
Print speed	A4 black: Up to 16 ppm; A4 color: Up to 4 ppm
	First page out (black, A4): As fast as 15.5 sec; First page out (color, A4): As fast as 27.5 sec Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims.
	Exact speed varies depending on the system configuration, software application, driver and document complexity.
Processor	Custom RISC processor
Memory	CP1025: 8 MB SDRAM, 128 MB Flash; CP1025nw: 64 MB SDRAM, 128 MB Flash;
Nemory upgrade	Not expandable
rint resolution	Up to 600 x 600 dpi
rint quality	HP ImageREt 2400
rinter languages	Host-based
ypefaces/fonts	Based on installed typefaces on host computer; installer installs 80 scalable TrueType screen fonts
Duty cycle (monthly, A4)	Up to 15,000 pages
ecommended Monthly Page Volume	200 to 850
Print margins	top: 4.3 mm, left: 4.3 mm, right: 4.3 mm, bottom: 4.3 mm Input Capacity Weight Size
Media handling	Tray 1         sheets: 150; labels: 50;         60 to 176 g/m² (plain paper); up to transparencies: 50; postcards: 50;         A4; A5; B5 (ISO, JIS); 76 x 127 to 2"           220 g/m² (glossy paper)         x 356 mm
	envelopes: 10 Duplex printing: Manual (driver support provided)
	Output: Sheets
	Envelopes: Up to 10 envelopes. Transparencies: Up to 50 transparencies; 50-sheet output bin
ledia types	Paper (bond, brochure, colour, glossy, letterhead, photo, plain, preprinted, prepunched, recycled, rough), transparencies, labels,
	envelopes, cardstock
ontrol Panel	CP1025: 6 buttons (Cancel, Resume, Cyan cartridge, Magenta cartridge, Yellow cartridge, Black cartridge); 6 LED indicator lights
	(Attention, Ready, Cartridge status for Cyan, Magenta, Yellow, Black); CP1025nw: 7 buttons (Cancel, Resume, Wireless, Cyan cartridge, Magenta cartridge, Yellow cartridge, Black cartridge); 7 LED indicator lights (Attention, Ready, Wireless, Cartridge status for Cyan, Magenta, Yellow, Black);
nterface and connectivity	CP1025:1 Hi-Speed USB 2.0; CP1025nw:1 Hi-Speed USB 2.0;1 Fast Ethernet 10/100Base-TX;1 Wireless 802.11b/g/n; optional: Compatible HP Jetdirect print servers: HP Jetdirect ew2500 802.11b/g Wireless Print Server J8021A
Network Capabilities	CP1025: Via optional, compatible HP Jetdirect Wireless Print Server; CP1025nw: Via built-in Fast Ethernet 10/100Base-TX networking or
	Wireless 802.11b/g/n;
obile printing capability	HP ePrint, HP wireless direct printing, Apple AirPrint™
upported Network Protocols	Via built-in networking solution: IPP, TCP/IP, IPv4, IPv6; print: TCP-IP port 9100 Direct Mode, LPD (raw queue support only), Web Service Printing; discovery: SLP, Bonjour, Web Services Discovery; IP Config: IPv4 (BootP, DHCP, AutoIP, Manual), IPv6 (Stateless Link-Local and via Router, Statefull via DHCPv6); management: SNMPv1, HTTP
Operating systems compatibility	Full software installs supported on: Windows 8, Windows 7 (32-bit and 64-bit), Windows Vista (32-bit and 64-bit), Windows XP (32-bit (SP2 or higher), Driver only installs supported on: Windows Server 2003 (32-bit) (SP3 or higher), Windows Server 2008 (32-bit and 64-bit); Mac OS X v10.5, 8, v10.6; Linpus Linux (9.4, 9.5), Red Hat Enterprise Linux 5.0 (supported with a pre-built package), SuSE Linux (10.3, 11.0, 11, 11.1, 11.2), Fedora (9, 9.0, 10, 10.0, 11.0, 11, 12, 12.0), Ubuntu <sup>®</sup> (8.04, 8.04.1, 8.04.2, 8.10, 9.04, 9.10, 10.04), Debia (5.0, 5.0.1, 5.0.2; 5.0.3) (supported by the automatic installer)
Network operating systems compatibility	Full software installs supported on: Windows 7 32-bit and 64-bit, Windows Vista 32-bit and 64-bit, Windows XP 32-bit (SP2 or higher
	Driver only installs supported or: Windows Server 2003 32-bit (SP3 or higher), Windows Server 2008 32-bit and 64-bit; Mac OS X v10.5.8, v10.6; Linpus Linux (9.4, 9.5), Red Hat Enterprise Linux 5.0 (supported with a pre-built package); SUSE Linux (10.3, 11.0, 11, 11.1, 11.2), Fedora (9, 9.0, 10, 10.0, 11.0, 11, 12, 12.0), Ubuntu <sup>®</sup> (8.04, 8.04.1, 8.04.2, 8.10, 9.04, 9.10, 10.04), Debian (5.0, 5.0.1, 5.0.2, 5.0.3) (supported by the automatic installer):
Minimum system requirements	Windows 8, Windows 7, Windows Vista: 1 GHz 32-bit(x86) or 64-bit(x64) processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 200 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows XP (32-bit) (SP2): Pentium® 233 MHz processor, 512 MI RAM (32-bit) or 2 GB RAM (64-bit), 200 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port, Mac OS X v10.5.8, v10.6; PowerPC G4, G5, or Intel® Core Processor; 256 MB RAM; 300 MB free hard disk space; CD/DVD-ROM or Internet; USB or Networl port
Software	Windows: HP Installer/Uninstaller, HP Raster print driver, HP Toolbox, HP Help and Learn Center; Mac: HP Installer/Uninstaller, HP Raster print driver, HP Utility
Printer management	Windows: HP Toolbox FX (default install); SNP Alerts (minimum install); HP Web Jetadmin (download); Mac: HP Utility
Power	Requirements: Input voltage: 220 to 240 VAC (+/- 10%), 50 Hz (+/- 3 Hz). Consumption: 295 watts (printing), 8 watts (ready), 3.1 watts
	(sleep), < 1 watt (auto-off), 0.2 watts (off); Typical Electricity Consumption (TEC): 0.925 kWh/Week
imensions (w x d x h)	Out of package: 399.6 x 402.1 x 251.5 mm Packaged: 498 x 298 x 387 mm
Veight	Out of package: 12.1 kg Packaged: 13.4 kg
Operating environment	Operating temperature: 15 to $32.5^{\circ}$ C; Recommended operating temperature: 20 to $27^{\circ}$ C; Operating humidity: 10 to 80% RH; Recommended operating humidity: 20 to 70% RH; Storage temperature: -20 to $40^{\circ}$ C; Storage humidity: 10 to 95% RH;
Product certifications	Safety certifications: IEC 60950-1: 2005 (International); EN 60950-1: 2006+A11 (EU); IEC 60825-1: 2007; GS License (Europe); EN 60825-1: 2007 (Class 1 Laser/LED Device); Low Voltage Directive 2006/95/EC with CE Marking (Europe); other safety approvals as required by individual countries; ENERGY STAR: Yes
Warranty	One-year, limited warranty, product exchange. Warranty and support options vary by product, country and local legal requirements.

http://www.hp.com/uk



© Copyright 2013 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.



#### Ordering information

)rderin	ng information	
F346A	HP Color LaserJet Pro CP1025 Printer;	
	introductory HP LaserJet Black, Cyan, Yellow,	
	Magenta print cartridges (pre-installed);	
	Imaging drum; CDs containing software and	
	electronic documentation; Documentation	
	(Install Guide, Support flyer, Warranty guide);	
	power cord	
E918A	HP Color LaserJet Pro CP1025nw Printer;	
	introductory HP LaserJet Black, Cyan, Yellow,	
	Magenta print cartridges (pre-installed);	
	Imaging drum; CDs containing software and	
	electronic documentation; Documentation	
	(Install Guide, Support flyer, Warranty guide);	
	power cord; USB cable	
	Supplies	
E310A	HP 126A Black Original LaserJet Toner Cartridge	
	Average continuous Black Cartridge yield 1200	
	standard pages. Declared yield value in	
	accordance with ISO/IEC 19798.	
E311A	HP 126A Cyan Original LaserJet Toner Cartridge	
	Average continuous composite	
	Cyan/Yellow/Magenta Cartridge yield 1000	
	standard pages. Declared yield value in	
	accordance with ISO/IEC 19798.	
E312A	HP 126A Yellow Original LaserJet Toner	
	Cartridge	
	Average continuous composite	
	Cyan/Yellow/Magenta Cartridge yield 1000	
	standard pages. Declared yield value in	
	accordance with ISO/IEC 19798.	
E313A	HP 126A Magenta Original LaserJet Toner	
	Cartridge	
	Average continuous composite	
	Cyan/Yellow/Magenta Cartridge yield 1000	
	standard pages. Declared yield value in	
	accordance with ISO/IEC 19798.	
E314A	HP 126A LaserJet Imaging Drum	
	14000 pages (black)7000 pages (colour)	
	Service & support	
M137E L	IP Care Pack, Exchange Service (standard	
	nd time), 3 years	
M133E HP Care Pack, Next Business Day Exchange		
ervice, 3 years		
M139E HP Care Pack, Return to Depot Exchange		
	6	

Om 139 FP Care Pack, Return to Deput Exchange Service, 3 years (UM137E: Austria, Belgium, Denmark, Finland, France, Germany, Ireland, Italy, Netherlands, Norway, Portugal, Spain, Sweden, Switzerland, UK. UM133E: Austria, Belgium, Denmark, Finland, France, Germany, Ireland, Italy, Netherlands, Norway, Portugal, Spain, Sweden, Switzerland, UK, Czech Republic, Greece, Hungary, Poland, Slovakia, UM139E: Baltics, Bulgaria, Czech Republic, Dom Tom, EEM, Greece, Hungary, Israel, Malta, MEMA, Moldova, Poland, Romania, South Africa, Russia, Slovakia, Slovenia, Turkey)

For a complete list of supplies, accessories and services, please refer to http://www.hp.com